

Is Now Part of



ON Semiconductor®

To learn more about ON Semiconductor, please visit our website at www.onsemi.com

Please note: As part of the Fairchild Semiconductor integration, some of the Fairchild orderable part numbers will need to change in order to meet ON Semiconductor's system requirements. Since the ON Semiconductor product management systems do not have the ability to manage part nomenclature that utilizes an underscore (_), the underscore (_) in the Fairchild part numbers will be changed to a dash (-). This document may contain device numbers with an underscore (_). Please check the ON Semiconductor website to verify the updated device numbers. The most current and up-to-date ordering information can be found at www.onsemi.com. Please email any questions regarding the system integration to Fairchild guestions@onsemi.com.

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any EDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officer



June 2003 Revised March 2004

NC7WV17

TinyLogic® ULP-A Dual Buffer with Schmitt Trigger Input

General Description

The NC7WV17 is a dual buffer with Schmitt trigger input from Fairchild's Ultra Low Power-A (ULP-A) Series of TinyLogic®. ULP-A is ideal for applications that require extreme high speed, high drive and low power. This product is designed for a wide low voltage operating range (0.9V to 3.6V V_{CC}) and applications that require more drive and speed than the TinyLogic ULP series, but still offer best in class low power operation.

The NC7WV17 is uniquely designed for optimized power and speed, and is fabricated with an advanced CMOS technology to achieve high-speed operation while maintaining low CMOS power dissipation.


Features

- 0.9V to 3.6V V_{CC} supply operation
- 3.6V overvoltage tolerant I/O's at V_{CC} from 0.9V to 3.6V
- Extremely High Speed t_{PD}
 - 1.5 ns typ for 2.7V to 3.6V $V_{\rm CC}$
 - 1.8 ns typ for 2.3V to 2.7V $V_{\rm CC}$
 - 2.0 ns typ for 1.65V to 1.95V V_{CC}
 - 3.2 ns typ for 1.4V to 1.6V V_{CC}
 - 5.9 ns typ for 1.1V to 1.3V V_{CC}
 - 12.0 ns typ for 0.9V $\ensuremath{\text{V}_{\text{CC}}}$
- Power-Off high impedance inputs and outputs
- High Static Drive (I_{OH}/I_{OL})
 - ±24 mA @ 3.00V V_{CC}
- ±18 mA @ 2.30V V_{CC}
- ±6 mA @ 1.65V V_{CC}
- ± 4 mA @ 1.4V V_{CC}
- ± 2 mA @ 1.1V V_{CC}
- $\pm 0.1 \text{ mA}$ @ 0.9V V_{CC}
- Uses patented Quiet Series[™] noise/EMI reduction circuitry
- Ultra small MicroPak™ leadfree package
- Ultra low dynamic power

Ordering Code:

Order Number	Package Number	Product Code Top Mark	Package Description	Supplied As
NC7WV17P6X	MAA06A	V17	6-Lead SC70, EIAJ SC88, 1.25mm Wide	3k Units on Tape and Reel
NC7WV17L6X	MAC06A	AX	6-Lead MicroPak, 1.0mm Wide	5k Units on Tape and Reel

Battery Life vs. V_{CC} Supply Voltage



TinyLogic ULP and ULP-A with up to 50% less power consumption can extend your battery life significantly. Battery Life = $(V_{battery}^{} *l_{battery}^{} *)/(P_{device})/24hrs/day$

Where, $P_{device} = (I_{CC} * V_{CC}) + (C_{PD} + C_L) * V_{CC}^2 * f$

Assumes ideal 3.6V Lithium Ion battery with current rating of 900mAH and derated 90% and device frequency at 10MHz, with C_L = 15 pF load

TinyLogic® is a registered trademark of Fairchild Semiconductor Corporation.

MicroPak™ and Quiet Series™ are trademarks of Fairchild Semiconductor Corporation.

Logic Symbol

IEEE/IEC



Pin Descriptions

Pin Names	Description
A ₁ , A ₂	Data Inputs
Y ₁ , Y ₂	Outputs

Function Table


$\mathbf{Y} = \mathbf{A}$

Input	Output
Α	Y
L	L
Н	Н


H = HIGH Logic Level L = LOW Logic Level

Connection Diagrams

Pin Assignments for SC70




Pin One Orientation Diagram



AAA represents Product Code Top Mark - see ordering code

Note: Orientation of Top Mark determines Pin One location. Read the top product code mark left to right, Pin One is the lower left pin (see diagram).

Pad Assignments for MicroPak



(Top Thru View)

±24 mA

Absolute Maximum Ratings(Note 1)

 $\begin{array}{lll} \mbox{Supply Voltage (V$_{CC}$)} & -0.5 \mbox{V to } +4.6 \mbox{V} \\ \mbox{DC Input Voltage (V$_{IN}$)} & -0.5 \mbox{V to } +4.6 \mbox{V} \\ \end{array}$

DC Output Voltage (V_{OUT})

 $\label{eq:local_$

DC Output Diode Current (I_{OK})

 $\begin{array}{lll} V_{OUT} < 0V & -50 \text{ mA} \\ V_{OUT} > V_{CC} & +50 \text{ mA} \\ \text{DC Output Source/Sink Current (I}_{OH}/I_{OL}) & \pm 50 \text{ mA} \\ \end{array}$

DC V_{CC} or Ground Current per

Supply Pin (I_{CC} or Ground) \pm 50 mA Storage Temperature Range (T_{STG}) -65° C to +150 $^{\circ}$ C

Recommended Operating Conditions (Note 3)

Supply Voltage 0.9V to 3.6VInput Voltage (V_{IN}) 0V to 3.6V

Output Voltage (V_{OUT})

 $V_{CC} = 0.0V$ 0V to 3.6V HIGH or LOW State 0V to V_{CC}

Output Current in I_{OH}/I_{OL} $V_{CC} = 3.0 \text{V to } 3.6 \text{V}$

 $\begin{array}{lll} {\rm V_{CC}} = 2.3 {\rm V} \; {\rm to} \; 2.7 {\rm V} & \pm 18 \; {\rm mA} \\ \\ {\rm V_{CC}} = 1.65 {\rm V} \; {\rm to} \; 1.95 {\rm V} & \pm 6 \; {\rm mA} \\ \\ {\rm V_{CC}} = 1.4 {\rm V} \; {\rm to} \; 1.6 {\rm V} & \pm 4 \; {\rm mA} \\ \\ {\rm V_{CC}} = 1.1 {\rm V} \; {\rm to} \; 1.3 {\rm V} & \pm 2 \; {\rm mA} \\ \end{array}$

 $V_{CC} = 0.9V \\ \mbox{Free Air Operating Temperature (T_A)} \\ \mbox{-40°C to +85°$C}$

Minimum Input Edge Rate (Δt/ΔV)

 $V_{IN} = 0.8V$ to 2.0V, $V_{CC} = 3.0V$ 10 ns/V

Note 1: Absolute Maximum Ratings: are those values beyond which the safety of the device cannot be guaranteed. The device should not be operated at these limits. The parametric values defined in the Electrical Characteristics tables are not guaranteed at the absolute maximum ratings. The "Recommended Operating Conditions" table will define the conditions for actual device operation.

Note 2: IO Absolute Maximum Rating must be observed.

Note 3: Unused inputs must be held HIGH or LOW. They may not float.

DC Electrical Characteristics

Symbol	Parameter	V _{CC}	T _A =	+25°C	T _A = -40°	C to +85°C	Units	Conditions
Зуппрог	Faranteter	(V)	Min	Max	Min	Max	Units	Conditions
V _P	Positive Threshold Voltage	0.90	0.3	0.7	0.3	0.7		
		1.10	0.4	1.0	0.4	1.0		
		1.40	0.5	1.4	0.5	1.4	V	
		1.65	0.7	1.5	0.7	1.5	v	
		2.30	1.0	1.8	1.0	1.8		
		2.70	1.5	2.2	1.5	2.2		
V _N Neg	Negative Threshold Voltage	0.90	0.10	0.6	0.10	0.6		
		1.10	0.15	0.7	0.15	0.7		
		1.40	0.20	8.0	0.20	8.0	V	
		1.65	0.25	0.9	0.25	0.9	v	
		2.30	0.4	1.15	0.4	1.15		
		2.70	0.6	1.5	0.6	1.5		
V _H	Hysteresis Voltage	0.90	0.07	0.5	0.07	0.5		
		1.10	0.08	0.6	0.08	0.6		
		1.40	0.09	8.0	0.09	8.0	V	
		1.65	0.15	1.0	0.15	1.0	v	
		2.30	0.25	1.1	0.25	1.1		
		2.70	0.60	1.2	0.60	1.2		

DC Electrical Characteristics (Continued)

Symbol	Parameter	V _{CC}	$T_A = +$	-25°C	$T_A = -40^{\circ}C \text{ to } +85^{\circ}C$		Units	Conditions
Symbol	Parameter	(V)	Min	Max	Min	Max	Units	Conditions
V _{OH}	HIGH Level	0.90	V _{CC} - 0.1		V _{CC} - 0.1			
	Output Voltage	$1.10 \le V_{CC} \le 1.30$	V _{CC} - 0.1		V _{CC} - 0.1			
		$1.40 \le V_{CC} \le 1.60$	V _{CC} - 0.2		V _{CC} - 0.2			1004
		$1.65 \le V_{CC} \le 1.95$	V _{CC} - 0.2		V _{CC} - 0.2			$I_{OH} = -100 \mu A$
		$2.30 \le V_{CC} < 2.70$	V _{CC} - 0.2		V _{CC} - 0.2			
		$2.70 \le V_{CC} \le 3.60$	V _{CC} - 0.2		V _{CC} - 0.2			
		$1.10 \le V_{CC} \le 1.30$	0.75 x V _{CC}		0.75 x V _{CC}			$I_{OH} = -2 \text{ mA}$
		$1.40 \le V_{CC} \le 1.60$	0.75 x V _{CC}		0.75 x V _{CC}		V	$I_{OH} = -4 \text{ mA}$
		$1.65 \le V_{CC} \le 1.95$	1.25		1.25			I _{OH} = -6 mA
		$2.30 \le V_{CC} < 2.70$	2.0		2.0			IOH0 IIIX
		$2.30 \le V_{CC} < 2.70$	1.8		1.8			I _{OH} = -12 mA
		$2.70 \leq V_{CC} \leq 3.60$	2.2		2.2			10H = -12 IIIA
		$2.30 \le V_{CC} < 2.70$	1.7		1.7			I _{OH} = -18 mA
		$2.70 \leq V_{CC} \leq 3.60$	2.4		2.4			IOH = -10 IIIA
		$2.70 \le V_{CC} \le 3.60$	2.2		2.2			$I_{OH} = -24 \text{ mA}$
V _{OL}	LOW Level	0.90		0.1		0.1		
	Output Voltage	$1.10 \le V_{CC} \le 1.30$		0.1		0.1		
		$1.40 \le V_{CC} \le 1.60$		0.2		0.2		$I_{OL} = 100 \mu A$
		$1.65 \le V_{CC} \le 1.95$		0.2		0.2		
		$2.30 \le V_{CC} < 2.70$		0.2		0.2		
		$2.70 \leq V_{CC} \leq 3.60$		0.2		0.2		
		$1.10 \le V_{CC} \le 1.30$		0.25 x V _{CC}		0.25 x V _{CC}	V	$I_{OL} = 2 \text{ mA}$
		$1.40 \le V_{CC} \le 1.60$		0.25 x V _{CC}		0.25 x V _{CC}		$I_{OL} = 4 \text{ mA}$
		$1.65 \le V_{CC} \le 1.95$		0.3		0.3		$I_{OL} = 6 \text{ mA}$
		$2.30 \le V_{CC} < 2.70$		0.4		0.4		I _{OL} = 12 mA
		$2.70 \leq V_{CC} \leq 3.60$		0.4		0.4		IOL = 12 III/
		$2.30 \le V_{CC} < 2.70$		0.6		0.6		I _{OL} = 18 mA
		$2.70 \leq V_{CC} \leq 3.60$		0.4		0.4		~-
		$2.70 \le V_{CC} \le 3.60$		0.55		0.55		$I_{OL} = 24 \text{ mA}$
I _{IN}	Input Leakage Current	0.90 to 3.60		±0.1		±0.5	μΑ	$0 \le V_1 \le 3.6V$
l _{OFF}	Power Off Leakage Current	0		0.5		0.5	μА	$0 \le (V_I, V_O) \le 3.6$
I _{CC}	Quiescent Supply Current	0.90 to 3.60		0.9		0.9	μА	$V_I = V_{CC}$ or GND
		0.90 to 3.60				±0.9	μι	$V_{CC} \le V_I \le 3.6V$

AC Electrical Characteristics

Symbol	Parameter	v _{cc}		Γ _A = +25°(2	$T_A = -40^{\circ}C$	C to +85°C	Units	Conditions	Figure
Cyllibol	i arameter	(V)	Min	Тур	Max	Min	Max	Oille	Conditions	Number
t _{PHL}	Propagation Delay	0.90		12					$C_L = 15 \text{ pF}, R_L = 1 \text{ M}\Omega$	
t _{PLH}		$1.10 \le V_{CC} \le 1.30$	2.0	5.9	14.5	1.0	19.9		C _L = 15 pF,	
		$1.40 \leq V_{CC} \leq 1.60$	1.0	3.2	7.0	0.9	7.5	ns	$R_L = 2 k\Omega$	Figures
		$1.65 \le V_{CC} \le 1.95$	1.0	2.0	5.2	0.7	6.2	115	C _L = 30 pF	1, 2
		$2.30 \leq V_{CC} < 2.70$	8.0	1.8	3.9	0.6	4.9		$R_L = 500\Omega$	
		$2.70 \leq V_{CC} \leq 3.60$	0.7	1.5	3.8	0.5	4.2			
C _{IN}	Input Capacitance	0		2.0				pF		
C _{OUT}	Output Capacitance	0		4.5				pF		
C _{PD}	Power Dissipation	0.90 to 3.60		14				pF	$V_I = 0V \text{ or } V_{CC}$	
	Capacitance	0.90 10 3.00		14				ÞΓ	f = 10 MHz	

AC Loading and Waveforms




FIGURE 1. AC Test Circuit





FIGURE 2. AC Waveforms


Symbol	V _{CC}								
- Cymbol	3.3V ± 0.3V	2.5V ± 0.2V	$1.8V \pm 0.15V$	1.5V ± 0.10V	1.2V ± 0.10V	0.9V			
V _{mi}	1.5V	V _{CC} /2							
V _{mo}	1.5V	V _{CC} /2							


Tape and Reel Specification TAPE FORMAT for \$C70

1741 = 1 014111741 101 4	30.0			
Package	Таре	Number	Cavity	Cover Tape
Designator	Section	Cavities	Status	Status
	Leader (Start End)	125 (typ)	Empty	Sealed
P6X	Carrier	3000	Filled	Sealed
	Trailer (Hub End)	75 (typ)	Empty	Sealed

TAPE DIMENSIONS inches (millimeters)








Packag	ge		Ta	ре		Number	Cavity	Cover Tape
Designa	itor			tion		Cavities	Status	Status
			Leader (S			125 (typ)	Empty	Sealed
L6X				rier		5000	Filled	Sealed
			Trailer (H	Hub End)		75 (typ)	Empty	Sealed
8.00 +0.30	2.00	4.00	(millimete	4.00	0.50±0.05	B ← DIRECTION OF FEED ← 0.254±0.020	3.50±0.05	1.15±0.05 ECTION B-B SCALE:10X
EL DIME	ENSION	S inches	 SEC	CALE:10X	0±0.05			
1			+					→ → w ₁
A —						TAPE SLOT	B C	N -
					TAIL X		LE: 3X	→ W ₃ → W ₂
ape size	Α	В	С	D	N		W2	W3
	7.0	0.059	0.512	0.795	2.165	0.331 + 0.059/-0.000	0.567	W1 + 0.078/-0.

Physical Dimensions inches (millimeters) unless otherwise noted



NOTES:

- A. CONFORMS TO EIAJ REGISTERED OUTLINE DRAWING SC88.
- B. DIMENSIONS DO NOT INCLUDE BURRS OR MOLD FLASH.
- C. DIMENSIONS ARE IN MILLIMETERS.


6-Lead SC70, EIAJ SC88, 1.25mm Wide

Package Number MAA06A

MAA06ARevC

www.fairchildsemi.com

Physical Dimensions inches (millimeters) unless otherwise noted (Continued)



Notes:

- 1. JEDEC PACKAGE REGISTRATION IS ANTICIPATED 2. DIMENSIONS ARE IN MILLIMETERS
- 3. DRAWING CONFORMS TO ASME Y14.5M-1994

MAC06ARevB

6-Lead MicroPak, 1.0mm Wide Package Number MAC06A

Fairchild does not assume any responsibility for use of any circuitry described, no circuit patent licenses are implied and Fairchild reserves the right at any time without notice to change said circuitry and specifications.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

- 1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
- 2. A critical component in any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

www.fairchildsemi.com

ON Semiconductor and in are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdt/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and exp

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor 19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800-282-9855 Toll Free USA/Canada
Europe, Middle East and Africa Technical Support:
Phone: 421 33 790 2910
Japan Customer Focus Center
Phone: 81-3-5817-1050

ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative